

IRB-EXP

EXPLOSIVE ENVIRONMENT PHOTOSWITCH

Applications

The IRB-EXP photocell is used as a safety, reversing, or opening device in conjunction with automatic operators. The IRB-EXP will work with any control board that accepts dry contact on the input. The easy to install IRB-EXP is used with garage doors, rolling doors, parking barriers and other equipment located in explosive environments.

IRB-EXP




EMX

INDUSTRIES


Erich Industries, Inc.
DoorSensors.com Division
sales@ErichIndustries.com
1-800-882-5839

IRB-EXP


- Designed to operate in areas with explosive environments
- NEMA 4 and 7 housing
- NEC Class I, Groups B, C & D, Class II, Groups E, F & G CSA certified, CENELEC certified, EExd IIC
- Copper free aluminum with epoxy finish
- Potentiometer range adjustment to allow more precise tuning to site
- Easy alignment and increased reliability
- Through beam design is not affected by shiny surfaces
- Modulated infrared to reduce the effect of sunlight, fog, rain, dust and dirt
- No focusing lens




Length / Width



Depth



Transmitter Board



Receiver Board

Technical Data

Power	12- 24volts AC or DC
Current	TX = < 21mA, RX = 23mA standby 17mA detect
Range	3 - 115 feet
Operating Temp	-40° F to +170° F
Relay Contact Rating	1A @ 24VDC or 120VAC
Housing Material	NEMA 4 & 7 Cast Aluminum
Dimensions	W – 4.69” x H – 4.5” x D – 3.44”
Detection Angle	18°
Gain Adjustment	Potentiometer
Certifications	CLASS I Groups B, C & D, CLASS II Groups E, F & G, CSA, CENELEC, EExd IIC

Erich Industries, Inc.
DoorSensors.com Division
sales@ErichIndustries.com
1-800-882-5839

Ordering Information

- IRB-EXP Infrared transmitter and receiver units

WARRANTY EMX INC. the product described herein for a period of 2 years under normal use and service from the date of sale to our customer. The product will be free from defects in material and workmanship. This warranty does not cover ordinary wear and tear, abuse, misuse, overloading, altered products, or damage caused by the purchaser from incorrect connections, or lightning damage. There is no warranty of merchantability. There are no warranties expressed, implied or any affirmation of fact or representation which extend beyond the description set forth herein. EMX Inc. sole responsibility and liability, and purchaser's exclusive remedy shall be limited to the repair or replacement at EMX's option of a part or parts not so conforming to the warranty. In no event shall EMX Inc. be liable for damages of any nature, including incidental or consequential damages, including but, not limited to any damages resulting from non-conformity defect in material or workmanship. Rev 2.3 07/28/14